

## 2023 PBA SCORPION 42



Oil Pattern Distance **Forward Oil Total Tank Configuration** 

42 17 mL A Only **Reverse Brush Drop Reverse Oil Total Tank A Conditioner** 

38 12.4 mL Oil Per Board **Volume Oil Total Tank B Conditioner** 

50 ul 29.4 mL

2 2L 2R 3 18 3 A 111 3.9 11.5 7.6 3 8L 8R 2 18 3 A 50 11.5 16.6 5.1 4 12L 10R 2 18 3 A 38 16.6 21.7 5.1	T.OIL										
2 2L 2R 3 18 3 A 111 3.9 11.5 7.6   3 8L 8R 2 18 3 A 50 11.5 16.6 5.1   4 12L 10R 2 18 3 A 38 16.6 21.7 5.1   5 14L 12R 2 18 3 A 30 21.7 26.8 5.1   6 2L 2R 0 18 3 A 0 26.8 34.0 7.2		FEET T.O	START END	CROSSED	TANK	BUFFER	SPEED	LOADS	STOP	START	
3 8L 8R 2 18 3 A 50 11.5 16.6 5.1   4 12L 10R 2 18 3 A 38 16.6 21.7 5.1   5 14L 12R 2 18 3 A 30 21.7 26.8 5.1   6 2L 2R 0 18 3 A 0 26.8 34.0 7.2	5550	3.9 55	0.0 3.9	111	Α	3	14	3	2R	2L	1
4 12L 10R 2 18 3 A 38 16.6 21.7 5.1 5 14L 12R 2 18 3 A 30 21.7 26.8 5.1 6 2L 2R 0 18 3 A 0 26.8 34.0 7.2	5550	7.6 55	3.9 11.5	111	Α	3	18	3	2R	2L	2
5 14L 12R 2 18 3 A 30 21.7 26.8 5.1 6 2L 2R 0 18 3 A 0 26.8 34.0 7.2	2500	5.1 25	11.5 16.6	50	Α	3	18	2	8R	8L	3
6 2L 2R 0 18 3 A 0 26.8 34.0 7.2	1900	5.1 19	16.6 21.7	38	Α	3	18	2	10R	12L	4
	1500	5.1 15	21.7 26.8	30	Α	3	18	2	12R	14L	5
7 2L 2R 0 22 3 A 0 34.0 42.0 8.0	0	7.2	26.8 34.0	0	Α	3	18	0	2R	2L	6
	0	8.0	34.0 42.0	0	Α	3	22	0	2R	2L	7

_												_
	START	STOP	LOADS	SPEED	BUFFER	TANK	CROSSED	START	END	FEET	T.OIL	
1	2L	2R	0	22	3	Α	0	42.0	35.0	-7.0	0	
2	13L	11R	2	22	3	Α	34	35.0	28.8	-6.2	1700	
3	11L	9R	3	22	3	Α	63	28.8	19.5	-9.3	3150	
4	9L	8R	2	18	3	Α	48	19.5	14.4	-5.1	2400	
5	5L	7R	1	18	3	Α	29	14.4	11.9	-2.5	1450	
6	2L	2R	2	18	3	Α	74	11.9	6.8	-5.1	3700	
7	2L	2R	0	14	3	Α	0	6.8	0.0	-6.8	0	

Cleaner Ratio Main Mix Cleaner Ratio Back End Mix Cleaner Ratio Back End Distance Buffer RPM: 4 = 700 | 3 = 500 | 2 = 200 | 1 = 100

NA NA NA Forward Reverse Combined



ltem	3L-7L:18L-18R	8L-12L:18L-18R	13L-17L:18L-18R	18L-18R:17R-13R	18L-18R:12R-8R	18L-18R:7R-3R
Description	Outside:Middle		Inside:Middle	Middle: Inside	Middle:Middle	Middle:Outside
Track Zone Ratio	2,56	1.55	1.02	1	1,24	2.68



